


## Agilent 33500B Series Waveform Generators

Agilent's 33500B Series of Waveform Generators with exclusive Trueform Technology offer more capability, fidelity and flexibility than traditional DDS waveform generators. Eight new upgradeable models are available at 20 and 30 MHz with 1- and 2-channels with a full set of standard features, and optional baseband I-Q signal player.



- Sine waves with 5x lower harmonic distortion
- Pulses up to 30 MHz with 10x less jitter
- Point-by-point arbitrary waveforms with sequencing
- 16 bits of resolution with 1 mVpp to 10 Vpp amplitude



### Key features and benefits:

- Superior signal integrity with Trueform technology providing highest resolution and lowest distortion
- Flexibility to select needed functionality from eight new value-priced models, with ability to upgrade later when your needs change
- Superior user experience with intuitive front panel, complimentary software and localized help and manuals, and access to manuals from mobile devices

### Key characteristics:

- Up to 30 MHz sine and pulse
- **Jitter:** < 40 ps
- **THD:** < 0.04%
- **Amplitude ranges:** 1 mVpp up to 10 Vpp
- 250 MSa/s sampling rate
- 16-bit amplitude resolution
- 1 MSa/channel memory, 16 MSa optional



## Quick Fact Sheet

### Agilent 33500B Series Waveform Generators

#### Step 1.

Choose your bandwidth, number of channels, and arbitrary waveforms

Waveform generator	33509B	33510B	33519B	33520B
Bandwidth	20 MHz	20 MHz	30 MHz	30 MHz
Number of channels	1	2	1	2

Waveform generator with arb	33511B	33512B	33521B	33522B
Bandwidth	20 MHz	20 MHz	30 MHz	30 MHz
Number of channels	1	2	1	2

#### Step 2.

Tailor your generator for more demanding applications

Application	Order option
Additional memory for long waveforms	MEM (only available on models with arb)
Baseband IQ Player with adjustments	IQP (only available on 33512B/33522B)
Security features with NISPOM	SEC
Ultra-high stability timebase	OCX

For more details on the *Agilent 33500B Series waveform generators*, see the brochure, Literature number: 5991-0757EN

For more information on *Agilent function/arbitrary waveform generators*, please visit: [www.agilent.com/find/functiongenerators](http://www.agilent.com/find/functiongenerators)

To find a distributor in your area, go to [www.agilent.com/find/distributors](http://www.agilent.com/find/distributors)

#### Recommended service options

Additional two years of Return-to-Agilent warranty  
 Additional two years of Return-to-Agilent calibrations  
 For more information go to [www.agilent.com/find/removealldoubt](http://www.agilent.com/find/removealldoubt)

#### Step 3.

Upgrade your waveform generator at any time as your needs change

Upgrade desired	Order upgrade option
Increase bandwidth to 30 MHz	335BW1U on 1-channel models 335BW2U on 2-channel models
Add arbitrary waveform capability	335ARB1U on 1-channel models 335ARB2U on 2-channel models
Add 16M memory to arb	335MEM1U on 1-channel arb models 335MEM2U on 2-channel arb models
Add NISPOM and file security	335SECU
Add IQ baseband signal player to 2-channel arb	335IQPU
Add high-stability timebase	33500U-OCX (Must return to Agilent)

*Note: Cannot upgrade a 1-channel generator to a 2-channel generator.*

